

EM 4100



Portable generators range: prompt power assistance to light up, tackle site jobs and property improvement works.

A complete range to choose from, for best solution to your remote power needs. When not fixing up around the job site, your portable generator can be used for emergency power during a power outage.

FEATURES

- · Powermate OHV engine provides consistent power for multiple applications
- Fuel: Petrol
- Starting Systems: Recoil
- Low-oil level shutdown automatically safeguards engine from damage Fuel gauge allows user to track gasoline levels
- AVR Automatic Voltage Regulator
- · Kit wheels integrated for easy transportation



PERFORMANCE		
Frequency	Hz	50
Voltage	V	230
Phase		1
Max Power	Watts	3500
Rated Power	Watts	3200




Engine		
Brand		Powermate
Туре		OHV
Operating Speed Nominal	rpm	3000
Fuel		Petrol
Starting Systems		Recoil
Oil capacity	I	0.6
Low Oil Shutdown		$\sqrt{}$



Alternator

Voltage regulation system AVR

Dimensional data		
Length	(L) mm	644
Width	(W) mm	545
Height	(H) mm	534
Dry weight	kg	53
Carton box dimension LxWxH	mm	620x452x495



Autonomy		
Fuel tank capacity		15
Fuel consumption 50%	l/h	1.8
Running time 50%	h	8



GENSET CONTROL PANELS

Mounted on the genset and complete of: instrumentation, control, protection of the generating set and sockets.

COMMANDS:

- Start selector switch OFF ON
- Recoil start

INSTRUMENTATION

- Voltmeter
- Fuel Level

PROTECTIONS:

- Thermal Circuit Breaker
- Oil Guard

SOCKET TYPE

SCHUKO 230V 16A IP44	2

The information is aligned with the Data file at the time of download. Printed on 01/12/2022 (ID 12770)

©2022 | PR INDUSTRIAL s.r.l. | All rights reserved | Image shown may not reflect actual package. Specifications subject to change without notice

